

- Ceph OSD Failed Disk** 3
- OSD Disk*** 3
- OSD Node 3
- Monitor Node 3
- OSD Node 3
- 가 3
- 4

Ceph OSD Failed Disk

Redhat Ceph storage 1.3 (Hammer)

Ceph OSD node 가 가

OSD Disk

OSD Node

```
[root@istgisd2]# ceph-disk list # <-  
[root@istgisd2]# /etc/init.d/ceph stop osd.28
```

Monitor Node

```
[root@istgmon1]# ceph osd out 28  
[root@istgmon1]# ceph -w # <-  
[root@istgmon1]# ceph osd crush remove osd.28  
[root@istgmon1]# ceph auth del osd.28  
[root@istgmon1]# ceph auth list  
[root@istgmon1]# ceph osd rm 28
```

OSD Node

```
[root@istgisd2]# umount /var/lib/ceph/osd/ceph-28
```

가

```
[root@istgisd2]# ceph-disk zap [ 가            ] ]  
[root@istgisd2]# ceph-disk prepare --fs-type xfs [ 가            ] ]  
[root@istgisd2]# ceph osd tree  
[root@istgisd2]# ceph-disk activate [ 가            ] ]
```

```
[root@istgosd2]# ceph-disk zap /dev/sdd
[root@istgosd2]# ceph-disk prepare --fs-type xfs /dev/sdd /dev/sdb2
[root@istgosd2]# ceph osd tree
[root@istgosd2]# ceph-disk activate /dev/sdd1
```

- <https://access.redhat.com/solutions/2127761>
- <https://access.redhat.com/solutions/1979363>
- <https://access.redhat.com/solutions/2158261>

From:

<https://atl.kr/dokuwiki/> - **AllThatLinux!**

Permanent link:

https://atl.kr/dokuwiki/doku.php/ceph_osd_failed_disk_%EA%B5%90%EC%B2%B4

Last update: **2019/05/14 05:13**

